



Amp_MPR series(Microwave)

MPR series(for Microwave) overview

MPR series is Pre-Amp with Low-Noise, High-Gain & wide-band, which is very effective to improve Dynamic range.

Parameter \ Type	MPR0106-33	MPR0126-32
Frequency range	1 - 6GHz	1 - 26.5GHz
Gain (dB)	33 (Min.)	32 (Min.)
VSWR (Typ.)	2:1	2.7:1
Noise Figure (dB Typ.)	< 2.5	< 4.5
Connector	N(f) In/Out	3.5(f) In/Out
Size (W x D x H)mm	160 x 230 x 95	
Weight	< 3Kg	
Power Supply	AC100V(±5%) 0.5A	

Customize available for frequency range, Gain, etc.

